

## Part Numbers:

Part Number	Description	Application
<b>415S1E-2.4</b>	<p>Suitable for 3-phase motors up to 1 kW (1.3HP). Thermal overload adjustable from 1.6-2.4Amps.</p> <ul style="list-style-type: none"> <li>• UP / DOWN / STOP external push buttons</li> <li>• External key switch</li> </ul>	Light Commercial Doors, Heavy Duty Cycle Roller Shutters, Sectional Doors, Garage and Sliding doors
<b>415S1E-4.0</b>	<p>Suitable for 3-phase motors up to 1.6kW (2.2HP). Thermal overload adjustable from 2.4-4.0Amps.</p> <ul style="list-style-type: none"> <li>• UP / DOWN / STOP external push buttons</li> <li>• External key switch</li> </ul>	Light Commercial Doors, Heavy Duty Cycle Roller Shutters, Sectional Doors, Garage and Sliding doors

### Key switch



**AUTO:** When the key is in the AUTO position the controller (motor) can be operated by:

- Wireless remote control
- Push button input on the circuit board which can be used to connect external push buttons, swipe card, loop detectors or keypads
- Pedestrian access input on the circuit board which can be used to connect external push buttons, swipe card, loop detectors or keypads
- Stop button on the front of the case

In AUTO mode the Open and Close button on the front of the case are disabled.

**OFF:** When the key is in the OFF position, the controller (motor) does not work. The push buttons and the wireless remotes are disabled.

**MANUAL:** When the key is in the MANUAL position the controller (motor) will only operate with the push buttons that are on the front panel. Wireless remote controls are disabled.